

## LineSelect® Model 8265 DB25 A/B Switch, Manual Operation, Desktop Unit

- **A Robust, High Integrity Switch**
- **No Power Required**

### INTRODUCTION

The **LineSelect®** Model 8265 allows the user to access two DB25 devices connected to the A and B ports from one DB25 device connected to the COMMON port. Switching between devices A and B is quick and easy via the front panel rotary selector - No need to plug and unplug cables. No chance for network reconfiguration errors. The **LineSelect®** Model 8265 is packaged in a compact desktop style enclosure.

### FEATURES:

- Allows access to two networks from one computer or workstation.
- High reliability sealed switch with self-wiping precious metal contacts.
- Eliminates the need to plug and unplug cables.
- No external power required.
- Transparent to data speed and format.
- Manual operation via front panel rotary switch.
- Attractive anodized black box packaging provides EMI/RFI shielding.
- Custom length DB25 cables available for your switch installation.
- Improves computer network efficiency by allowing sharing of peripherals.
- Lifetime guarantee against manufacturing defects.
- **Switches pins 2 through 25 of the DB25 interface. All pins 1(Protective Ground) are tied together and bussed through to eliminate surges.**
- Plenum rated insulation on all internal wiring.
- Connector shells are bussed together.
- Rear panel chassis stud accepts spade lug for secure grounding.



### SPECIFICATIONS:

#### PORT CONNECTORS:

(3) DB25 female connectors labeled A, B, and COMMON.

#### FRONT PANEL CONTROLS:

(1) Rotary Switch allows local switching.

POWER: Manually operated. No power required.

#### GROUND STUD: On rear panel.

**DIMENSIONS:** 5.25"W x 2.62"H x 7.8"D.  
(13.3 x 5.1 x 18.4 cm)

**WEIGHT:** Approximately 1.2 lb. (0.6 kg.)

- **Also available with no feet. See Model 8266, Cat. No. 304161.**

### LineSelect® Model 8265 DB25 A/B Switch Application

