

LineSelect® Model 8267 DB25 A/B Switch, Manual Operation, via Keylock, Desktop

- **Key Operated Control Provides Secure A/B Switching.**
- **Robust, High Integrity Switch.**
- **No Power Required.**

INTRODUCTION

The **LineSelect®** Model 8267 DB25 A/B Switch allows the user to access two DB25 devices connected to the A and B ports from one DB25 device connected to the COMMON port. Switching between devices A and B is quick and easy via the front panel keylock switch. The **LineSelect®** Model 8267 is packaged in a slim desktop style enclosure.

FEATURES:

- Allows access to two networks from one computer or workstation.
- High reliability sealed switch with self-wiping precious metal contacts.
- Eliminates the need to plug and unplug cables.
- No external power required.
- Transparent to data speed and format.
- **Manual operation via front panel keylock switch.**
- **Key is captive in position B.**
- **Key can only be removed in the A position**
- All (25) pins of the DB25 interface are switched via a break-before-make rotary switch.
- Attractive anodized aluminum black box packaging provides EMI/RFI shielding.
- Chassis has no feet.
- **Rear panel chassis stud accepts spade lug for secure grounding.**
- Custom length DB25 cables available for your switch installation.
- Improves computer network efficiency by allowing sharing of peripherals.
- Lifetime guarantee against manufacturing defects.



SPECIFICATIONS:

PORT CONNECTORS:

(3) DB25 female connectors labeled A, B, and COMMON.

FRONT PANEL CONTROLS:

(1) Keylock Switch allows local switching.

POWER: Manually operated. No power required.

GROUND STUD: On rear panel.

DIMENSIONS: 5.44"W x 2.02"H x 7.27"D. (13.9 x 5.2 x 18.5 cm)

WEIGHT: Approximately 1.5 lb. (0.7 kg.)

LineSelect® Model 8267 A/B Keylock Application

