

LineSelect® Model 9500 5-Channel Manual Switch (4 channels DB25 A/B and 1 channel RJ11/12 A/B/C/D), Rackmount Configuration

- Five channels of switching packed in a 2U, 19-inch standard rackmount enclosure.

INTRODUCTION

The LineSelect® Model 9500 5-Channel Manual Switch provides the user with four channels of DB25 A/B switching, and one channel of RJ11/12 A/B/C/D switching. Each channel is individually operated via its front panel rotary switch. No power is required.

FEATURES

- Each of four DB25 A/B channels allow quick connection to any one of two DB25 interface devices from one COMMON port.
- One RJ11/12 A/B/C/D channel allows quick connection to any one of four RJ11/12 interface devices from one COMMON device.
- All 25 pins of the DB25 interface are switched via break-before-make rotary switch.
- All 6 pins of the RJ11/12 interface are switched via break-before-make rotary switch.
- High quality sealed switch with self-wiping low impedance contacts.
- Transparent to data speed and format.
- **Independently switch each of five channels via knobs on front panel.**
- Eliminates the need to plug and unplug cables.
- No external power is required.
- Attractive all metal, black box packaging provides EMI/RFI shielding.
- **Lifetime guarantee against manufacturing defects.**
- Custom length cables available for your switch installation.



SPECIFICATIONS:

PORT CONNECTORS: (12) DB25 female connectors. (Three connectors labeled A, B, and COMMON for each of four channels).

(5) RJ11/12 female connectors labeled A, B, C, and COMMON.

FRONT PANEL CONTROLS: (4) Rotary switches on front panel, one knob per channel, to switch each channel independently.

(1) Rotary switch on front panel selects A, B, C, or D.

POWER: No power is required.

DIMENSIONS: Rackmount configuration 19.0" W x 3.5" H x 8.04" D. (48.3 x 8.9 x 22.4 cm)

WEIGHT: Approximately 5.7 lbs. (2.6 kg)

LineSelect® Model 9500 Four Independent DB25 A/B Switches & One RJ11/12 A/B/C/D Switch Application

