

LineSelect® Model 4546 Quad Channel Phoenix Connector A/B Switch, Rackmount, Manual Operation.

INTRODUCTION

The *LineSelect*® Model 4546 Quad Channel Phoenix Connector A/B Switch enables access to two devices per each of its four channels. All ports of channels one and two utilize 12-Pin Phoenix connectors. All ports of channels three and four utilize 10-Pin Phoenix connectors. All four channels switch simultaneously.

FEATURES:

- Each of the four channels allows quick connection to any one of two devices from one COMMON device.
- Manual operation via front-panel rotary switch.
- Simultaneously switches all four channels.
- All pins of the Phoenix interface are switched.
- High quality sealed switch with self-wiping low impedance contacts.
- Transparent to data speed and format.
- Improves network efficiency by allowing sharing of peripherals.
- Eliminates the need to plug and unplug cables.
- No external power required.
- Attractive anodized black box packaging provides EMI/RFI shielding.
- Custom Length Phoenix cables available for your installation.
- Lifetime guarantee against manufacturing defects.



SPECIFICATIONS:

CHANNEL 1 and 2 PORT CONNECTORS:

Channels one and two each have (3) female 12-pin Phoenix connectors labeled "A", "B", and "COM".

CHANNEL 3 and 4 PORT CONNECTORS:

Channels three and four each have (3) female 10-Pin Phoenix connectors labeled "A", "B", and "COM".

POWER: No power required. Manually Operated.

DIMENSIONS: Rackmount 19" W x 3.5" H x 8.8" D.
(48.3 x 8.9 x 20.3 cm)

WEIGHT: Approximately 5.1 lbs. (2.3 kg)

LineSelect® Model 4546 Quad Channel Phoenix Connector A/B Switch Application:

